CAMBRIDGE INTERNATIONAL EXAMINATIONS

Cambridge International Advanced Level

www.PapaCambridge.com MARK SCHEME for the October/November 2014 series

9691 COMPUTING

9691/31

Paper 3 (Written Paper), maximum raw mark 90

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge will not enter into discussions about these mark schemes.

Cambridge is publishing the mark schemes for the October/November 2014 series for most Cambridge IGCSE®, Cambridge International A and AS Level components and some Cambridge O Level components.

® IGCSE is the registered trademark of Cambridge International Examinations.

(a) (i) a b + 6 /

X

- (ii) 3 <u>x y * 3 +</u> *
- **(b) (i)** 3 * (x + y + z)

(ii)
$$(7^y + 6) / 2$$

1 mark only for:

- 7^y or...
- $(7^{y} = 6) / 2$

[2]

(c) (i) Last item added is the first to leave // first add will be the last to leave Last in - First out // First in - Last out Refuse: LIFO

[1]

(ii) 5 4 3 8 2 14 6 14 1

[max 4]

(a) The main memory is divided into page frames

The program is divided into pages

Only some of the pages of the program are loaded to start execution of the program The operating system must manage the allocation of pages to page frames

The Page (Map) table shows the mapping of pages to page frames


[max 3]


(b) 'Priority' which is well explained and clear \times 2 E.g. Anticipated shortest time to complete Shortest remaining time to complete

[max 2]

(c) Mark as follows...

B – D – F – A or	Scores full 4	Tage
C and E are excluded	1	
В	1	
D	1	
F	1	
A each in the correct position	1	[max 4]





2 X correct relationship

(iii) A customer can never purchase more than one painting on the same date [1]

[2]

CustomerName is known from only CustomerID // CustomerName will be known by only knowing part of the primary key 1

[3] Sales(CustomerID, PurchaseDate, PaintingID) 1

1 (ii) Not in 3NF... - Painting

There are non-key attributes which are dependent. Or by example...

DateBorn/DateDied/Nationality are all dependant on ArtistName 1

Painting(PaintingID, Description, PaintingDate, ArtistName, Price)

Artist(ArtistName, ArtistDateBorn, ArtistDateDied, ArtistNationality)

Mark as follows:

All except ArtistName removed from table Painting	1	
New table Artist	1	
Artist containts at least three of the correct attributes	1	[5]

Р	Page 4		Mark Scheme	Syl Syl	er
			Cambridge International A Level – October/November 2014	969 ADAC	
		WH:	ERE CustomerID = "065"	969 ADACAM	Brid
4	(a)	(i)	ACC = 77 Show contents of 203 copied to ACC	1 1	[2]
		(ii)	ACC = 65 Show 150 used as a forwarding address Contents of 200 copied to ACC	1 1 1	[3]
	(b)	(i)	256 different instructions		[1]
		(ii)	Store the ACC contents at address 65 // 01000001	1 1	[2]
		(iii)	Fewer digits to write // less chance of an error in writing the code // to/from binary code	easy conversion	[1]
		(iv)	1041 hex		[1]
		(v)	LDI 150		
		(vi)	Opcode Operand LDV 15	1 1	[2]
			0 0 0 0 0 1 0 1 0 0 0 1 1 1		
			Opcode Operand	1 1	[2]
	((vii)	True OUTCH / IN // END or using a good explanation (only) of either		[2]

Page 5			Mark Scheme)	Sy. per
	Cambri	idge Internatior	nal A Level – O	ctober/November 2014	969
(c) [ACC	Location 150	OUTPUT	٦	Cambridge
(-)	ACC	Location 150	OUTFUT		Dr.
	65		A		198
-	200				, G
-	201	201			On
-					
	7.0		T	4	

ACC	Location 150	OUTPUT	
65		A	
200			
201	201		
76		L	
201			
202	202		
65		A	
202			
203	203		
77		M	
203			
204	204		

Mark as shown [5]

5 (a) a single processor

program consists of a sequence of stored instructions 1 1 instructions + data make up a 'program' are stored in a continuous block of main memory 1 1 instructions are executed in sequence

- **(b)** 1. The (contents of) the program counter/PC are copied to the Memory Address Register
 - The contents of the Program Counter are incremented
 - 3. Identify the address in the Memory Address Register. Go to this address and copy its contents to the Memory Data Register
 - 4. The (contents of) the Memory Data Register are copied to the <u>Current Instruction</u> [4] Register
- (c) (i) Control bus [1]
 - (ii) read/write interrupt reset clock signal bus request/bus grant

[max 1]

[max 2]

Pa	ige (6	Mark Scheme S	969 Add	per
			Cambridge International A Level – October/November 2014	969	6
	(d)	(i)		1	Cannonida
		(ii)	Case 2	1	9
			The instruction is for directed addressing The address bus is loaded with address 35	1	[2]
6	(a)	(i)	All the keyboards which make up the syntax of the language A token for each keyword	1 1	[2]
		(ii)	DECLARE, CONSTANT, CALL, REPEAT (any three)		[1]
		(iii)	A list of all the identifiers used by the program A pointer to where their value is stored in memory	1 1	[2]
		(iv)	<pre>i, Customer, Address, DiscountRate, InitialiseCusto (any three)</pre>	omerData	[1]
		(v)	Lexical analysis remove any whitespace from the source file remove any comment statements check for obvious errors in the use of identifiers (names) e.g. they do exceed 64 characters replace all language keywords with their token (by searching for the appropriate keyword in the keyword table) place an identifier names in the symbol table search for the appropriate identifier in the symbol table – the identifie is replaced in the source code by a pointer value	1 1 1	[5]
	(b)	(i)	Code optimisation the process of taking the final executable code produced by the component in some way	1	
			in order that it will use fewer resources // less memory Refuse: reduced in size	1	
			it will execute faster removes redundant code	1 1	[max 2]
		(ii)	203		[1]

		7.
Page 7	Mark Scheme	Syl oer
	Cambridge International A Level – October/November 2014	969

7 (a) 3 (days)

(b) Error

(c) 2 (months) [1]

(d) Error [1]

(e) Error [1]

(f) Built-in functions are those provided (as a part of the programming language) // accept by example 1
User defined functions are designed and coded by the programmer 1 [2]